



Flight Light Inc.  
2708 47th Ave.  
Sacramento, California, U.S.A.  
95822-3806

PH (916) 394-2800 FX (916) 394-2809  
TF (800) 806-3548 EM info@flightlight.com

## Lamps for Airfield Applications



Fig. 1




Fig. 2



Fig. 3



Fig. 4



Fig. 5



Fig. 6



Fig. 7



Fig. 8



Fig. 9



Fig. 10

Fig.	Part number	MOL	Watt	Description	Lamp Life (hrs)	Case
1	LA-12V/20W	1.5"(T2.5)	20	Qtz Lamp Assembly (for LOVA signs)	2000	N/A
2	LA-11478	1.75"(T3.5)	30	6.6A, EXL, Qtz	1000	24
2	LA-11482	1.75"(T3.5)	45	6.6A, EXM, Qtz	1000	24
3	LA-10099	2.5"(T4)	120	6.6A, EVV, Qtz	500	24
3	LA-11427	2.5"(T4)	150	6.6A, EWR, Qtz	500	24
3	LA-15243	2.5"(T4)	200	6.6A, EZL, Qtz	500	24
3	LA-40702	2.5"(T4)	200	6.6A, Q200T4/CL, GY9.5	500	12
3	LA-40925	2.5"(T4)	150	6.6A, EWR, Qtz, GZ9.5	500	24
3	LA-41541	2.5"(T4)	45	6.6A, Q45T4CL	500	12
4	LA-6134	1.85"(T4)	45	6.6A EXM, Bi-pin, GZ9.5	1500	100
4	LA-6292	2.44"(T4)	150	6.6A, EWR, GY9.5, Qtz	750	
4	LA-6372	2.44"(T4)	200	6.6A, EZL, Bi-pin, GZ9.5	750	100
5	LA-88525	9-1/4"(T20)	1000	120V, 1M/T20/BP, Mogul Bi-Post (G38)	250	12
6	LA-6343	1.85"(T4)	100	6.6A, G6.35, Qtz	1200	
6	LA-6373	1.85"(T4)	200	6.6A, G6.35, Qtz	1200	
6	LA-J1/57	1.85"(T4)	45	6.6A, G6.35, Qtz	1200	100
6	LA-J1/58	1.85"(T4)	100	6.6A, G6.35, Qtz	1200	100
6	LA-J1/75	1.85"(T4)	36	6.6A, G6.35, Qtz	1200	100
7	LA-6130	2.3"(T4)	45	6.6A, PK30d, female leads	1000	
7	LA-59079	2.3"(T4)	150	6.6A, PK30d, male leads	1000	
7	LA-64341Z	2.3"(T4)	100	6.6A, PK30d, male leads	1000	
7	LA-J1/76	2.3"(T4)	45	6.6A, PK30d, male leads	1000	
7	LA-J1/77	2.3"(T4)	45	6.6A, PK30d, male leads	1000	
7	LA-J1/80	2.3"(T4)	100	6.6A, PK30d, male leads	1000	
7	LA-J1/83	2.3"(T4)	150	6.6A, PK30d, female leads	1000	
8	LA-6303 LL	2.283"	45	6.6A, Pk30d, male leads	2000	100
8	LA-6313	2.283"	200	6.6A, PK30d, male leads	1000	
8	LA-6392 LL	2.283"	150	6.6A, PKX30d, male leads	2000	100
9	LA-14473	2-3/8"(T4)	45	6.6A, Qtz, DCR		
9	LA-23860	2-3/8"(T4)	200	6.6A, Qtz, DCR	500	12
10	LA-23710	2.56"(T4)	150	Q150T4/CL	3000	12

T=Tube. Multiply T# by 1/8" to get diameter.

Visit our web site: [www.flightlight.com](http://www.flightlight.com)



Flight Light Inc.  
 2708 47th Ave.  
 Sacramento, California, U.S.A.  
 95822-3806

PH (916) 394-2800  
 TF (800) 806-3548

FX (916) 394-2809  
 EM info@flightlight.com

## Lamps for Airfield Applications



Fig. 11



Fig. 12



Fig. 13



Fig. 14



Fig. 15



Fig. 16



Fig. 17



Fig. 18



Fig. 19



Fig. 20

Fig.	Part number	MOL	Watt	Description	Lamp Life (hrs)	Case
11	LA-J1/78	1.87"	45	45W, 6.6A, R7s	1000	100
12	LA-6142	1.77"(MR16)	62	6.6A, MR16, Bi-Pin, GX5.3	1500	100
12	LA-20590	1-7/8"(MR16)	62	6.6A, MR16, without leads		
12	LA-20839	1-7/8"(MR16)	50	Q50MR16/NSP-12V	6000	20
12	LA-23071	1-7/8"(MR16)	45	6.6A, MR16, EZC	1000	20
13	LA-64826	1-7/8"(MR16)	50	MR16, 230V		
14	LA-008084	1-7/8"(MR16)	50	MR16, 120V	2000	15
15	LA-008065	1-7/8"(MR16)	48/49	6.6A, twin male leads	1500	
15	LA-008072	1-7/8"(MR16)	105	6.6A, twin male leads	1500	
15	LA-008075	1-7/8"(MR16)	105	6.6A, twin female leads	1500	
15	LA-008079	1-7/8"(MR16)	48	6.6A, MR16, twin female leads	1500	
15	LA-20624	1-7/8"(MR16)	62	6.6A, MR16, with 12" female leads		
16	LA-6101	1.77"(MR16)	48	6.6A, MR16, female leads	1500	
16	LA-6104	1.46"(MR11)	40	6.6A, MR11, male leads	1500	
16	LA-6138	1.77"(MR16)	48	6.6A, MR16, cable male/female connectors	500	100
16	LA-6141	(MR16)	62	6.6A, MR16, cable, flat female	1500	100
16	LA-LA000011	1-7/8"(MR16)	48	6.6A, MR16, male/female leads, insulating sleeve	1000	
17	LA-6105	1.77"(MR16)	105	6.6A, MR16, female/female, cable flat female	1000	
17	LA-LA000004	1-7/8"(MR16)	105	6.6A, MR16, male/female leads, insulating sleeve	1000	
18	LA-7654H	3.85"(T10)	45	6.6A, T10, P28s	2000	100
18	LA-7669H	3.85"(T10)	30	6.6A, T10, P28s	2000	100
19	LA-23294	3-15/16"(T10)	30	6.6A, T10/1P	1000	60
19	LA-23295	3-15/16"(T10)	45	6.6A, T10/1P	1000	60
20	LA-23300	5.75"(T14)	204	6.6A, T14/2P	500	24

T=Tube. Multiply T# by 1/8" to get diameter.

Visit our web site: [www.flightlight.com](http://www.flightlight.com)



Flight Light Inc.  
 2708 47th Ave.  
 Sacramento, California, U.S.A.  
 95822-3806

PH (916) 394-2800 FX (916) 394-2809  
 TF (800) 806-3548 EM info@flightlight.com

## Lamps for Airfield Applications



Fig. 21



Fig. 22



Fig. 23



Fig. 24



Fig. 25



Fig. 26



Fig. 27



Fig. 28



Fig. 29



Fig. 30

Fig.	Part number	MOL	Watt	Description	Lamp Life (hrs)	Case
21	LA-10387	5.25", PAR38	120	120V, PAR38		
21	LA-15937	5.25", PAR38	45	6.6A, PAR38	800	12
21	LA-16138	5.3"(D=4.75")PAR38	75	120V, PAR38, E26, Qtz	2500	
21	LA-18631	5.31", PAR38	100	100PAR38/HIR/FL25	3000	12
22	LA-23310	4.5"(D=7")PAR56	45	6.6A, PAR56/5	1000	12
22	LA-23863	4.5"(D=7")PAR56	500	Q20A, PAR56/3	500	12
22	LA-32861	4.5"(D=7")PAR56	300	Q20A, PAR56/2	500	12
22	LA-PAR56/120W/H	4.5"(D=7")PAR56	120	Strobe, PAR56	1000	12
22	LA-PAR56/3	4.5"(D=7")PAR56	200	Q6.6A, PAR56/3		
23	LA-15482	5"(D=7")PAR56	300	Q20A, PAR56/C	500	12
23	LA-15485	5"(D=7")PAR56	500	Q20A, PAR56/1/C	500	12
23	LA-38271	5"(D=7")PAR56	200	Q6.6A, PAR56/2	1000	12
24	LA-13224	4.5"(D=8")PAR64	200	Q6.6A, PAR64/2P(VASI)	2000	6
24	LA-43497	4.5"(D=8")PAR64	1000	Q1000PAR64-NSP-120V	4000	6
25	LA-116w/230	(A21)	116	230V, A21, screw base	8000	
25	LA-12496-1	4.37"(A21)	69	120V, 69A21/TS, screw base	8000	
25	LA-16385	4-3/8"(A21)	50	50A21, 30V(sign)	1000	120
25	LA-16997	4-7/8"(A21)	60	60A21/B	1000	120
25	LA-17625	5-1/4"(A21)	150	150A21/RS	1000	60
25	LA-17960	4-3/8"(A21)	54	60A21/54WM/TS	8000	120
25	LA-22483-2	4.44"(A21)	116	120V, A21/TS, screw base	8000	
25	LA-97470	4-7/16"(A19)	40	40A/CL, 24PK, 120V	1500	120
26	LA-21950	10-7/16"(PS40)	620	620PS40P, 120V	3000	24
26	LA-700120	10-7/16"(PS40)	700	700PS40P, 120V		
26	LA-700230	10-7/16"(PS40)	700	700PS40P, 230V	8000	
27	LA-FT-152	2.5"	N/A	Strobe FT		
28	LA-18902	5.75"	175	MVR175/U/MED	6000	6
29	LA-43828	11.5"	400	MVR400/U	15000	6
30	LA-44058	15.06"	1000	LU1000/ECO	+24000	6

**If you don't see what you need - call us and we will find it for you!**

Flight Light stocks lamps for all airport lighting applications: runway, taxiway, approach, helipad, obstruction. We sell only first quality name-brand lamps, including GE, Osram/Sylvania, Philips and Amglo.

Visit our web site: [www.flightlight.com](http://www.flightlight.com)